



ARCO  
Indoor Emergency Lighting

CE Certificate Number  
00122/101/1/2017

ENEC Approved

# ARCO

## Indoor Emergency Lighting



### General Specifications

- Indoor luminaire for wall or ceiling mounting.
- Fancy design that blends in effortlessly with modern spaces.
- Unique design with 3 distinct light elements arranged in an arc.
- Built-in self-test feature.
- Can be used for Emergency lighting (non-maintained) and also for Ambient lighting (maintained).
- Easy identification of Faults (battery, lighting elements).
- Easy installation and easy battery replacement.
- Five (5) luminance levels for each operating mode.
- ENEC approved. Certified to EN60598.

### Technical Specifications

Power Supply:	<b>230VAC/50Hz</b>
Max. Power Consumption:	<b>Less than 5VA</b>
Light Source:	<b>12 LED</b>
Battery:	<b>3.6V 1.0Ah NiCd</b>
Emergency Operation Time:	<b>From 180min to 240min depending on luminance setting</b>
Luminance setting:	<b>5 steps (20, 40, 60, 80 &amp; 100%)</b>
Light source intensity (230V):	<b>100lm</b>
Mounting:	<b>Wall/ceiling</b>
Switch over Voltage:	<b>Between 150 ~ 190V</b>
IP rating:	<b>IP20</b>
Isolation Category:	<b>Double isolation</b>
Environmental:	<b>Temperature: +5 to 45 °C, Humidity: 5 to 95% RH, non condensating</b>
Dimensions [WxHxD]:	<b>225x100x47 mm</b>
Guarantee:	<b>3 years (1 year for the battery)</b>

