



## **ELIX**Indoor Emergency Lighting

CE Certificate Number 00114/101/1/2017

ENEC Approved

## **ELIX**

## **Indoor Emergency Lighting**

## **General Specifications**

- · Indoor luminaire for wall mounting.
- · Control and programming button.
- 3 x status LEDs and reset button.
- · Built-in self-test feature.
- Can be used for Emergency lighting (non-maintained) and also for Ambient lighting (maintained).
- Easy identification of Faults (battery, lighting elements).
- Slim design (only 27mm depth).
- · Easy installation and easy battery replacement.
- Five (5) luminance levels for each operating mode.
- ENEC approved. Certified to EN60598.
- Left, right and down pointing arrow stickers are included.





Power Supply:	230VAC/50Hz
Max. Power Consumption:	Less than 5VA
Light Source:	12 LED
Battery:	3.6V 1.0Ah NiCd
Emergency Operation Time:	From 150 min to 240 min depending on luminance setting
Luminance setting:	5 steps (20, 40, 60, 80 & 100%)
Light source intensity (230V):	100lm
Mounting:	Wall
Switch over Voltage:	Between 150 ~ 190V
IP rating:	IP20
Isolation Category:	Double isolation
Environmental:	Temperature: +5 to 45 °C Humidity: 5 to 95% RH, non con-
	densating
Indication Area Dimensions [WxHxD]:	228x75 mm
Dimensions [WxHxD]:	260x125x33.5 mm
Guarantee:	3 years (1 year for the battery)





